



rammount.com

1-800-497-7479

sales@rammount.com

RAM® Remote Speaker Mic with Sonim SecureAudio Connector

Part # RAM-RSM-SNM1

UPC 793442035685

Price \$158.49



OVERVIEW

The RAM® Remote Speaker Mic with Sonim SecureAudio Connector (RAM-RSM-SNM1) delivers clear, reliable push-to-talk (PTT) and speaker functionality through a Sonim SecureAudio connection. Designed for field operators who prefer an all-in-one PTT solution, this lightweight remote speaker microphone pairs seamlessly with any Sonim phone and RAM® docking solution—ideal for public safety, utility services, logistics, delivery fleets, and more.

FEATURES

- 2-in-1 microphone and speaker for amplified audio and push-to-talk (PTT)
- Uses a Sonim SecureAudio connector for reliable PTT when paired with a Sonim phone
- Lightweight and simple design with clear access to volume buttons, audio port, and PTT button
- Backed by a 3-year warranty

SPECIFICATIONS

Hardware Included	(1) Microphone (1) Mounting Clip & Hardware
Speaker Specifications	Max Volume Level: 94db +/- 3DB (@1000-2000HZ) Impedance: 12 OHM (+/- 15%) Rated Noise Power for 100hrs: 1.5W @ 4.24VDC Long Term Max Power 1min On / 2min Off: 2W @ 4.90VDC
Packaging Type	Poly Bag

Power Specifications	Operating Voltage: 1.2VDC - 5VDC Current Consumption 100UA - 500UA Output Impedance @ 1KHZ Max 2.2K Ohms Signal to Noise Ratio: 1KHZ 60+ DB Max Input SPL 110DB Moisture Ingress Rating IP67
Operating Temperature	-10°C to +55°C
Ports	3.5mm TS Female - Mono Audio Out Only
Certifications	IP67, IPCWHAA-A-620B Pull Strength USB-IF Certified FCC, UKCA, CE (RED), RoHS, WEEE, IC
Weight	0.44 lb

rammount.com/products/ram-rsm-snm1